



DJ MONITOR

PG-45



After extensive development and consulting with some of the world's best DJs, we are proud to announce the new PG-45 DJ monitoring system. This unique direct impact system consists of a 15" coaxial and a double 15" sub, custom made radial drivers. Our unique drivers feature three cooling systems, an enhanced vented magnet, a multi-finned front plate, magnet inter-cooler and finally the patented external radio chassis that works as a giant heatsink.

This keeps voice coil and magnet temperatures exceptionally low resulting in superb reliability, 3 dB less power compression and tight clean bass even after prolonged operation at maximum power. It has a symmetrical field magnet with extended center pole for absolute linearity and transient control on high power peak inputs. It has double rear suspensions for stability and a four layer voice coil to maximize BL.

The unique coaxial box has four different angles for multiple configurations so they can easily be adjusted depending on the height of the artist and desired distance in between.



COAX	
DRIVER	1x15" Custom Radial Coaxial Driver, 1.4" HF driver [4" coil]
CONINUOUS OUTPUT	133db
PEAK OUTPUT	136db
DIMENSIONS	18"H x 18"W x 18"D
WEIGHT	62 lbs
RATED IMPEDANCE	8ohm
FREQUENCY RESPONSE	82 - 20,000 hz
POWER RATING	600w AES
CROSSOVER	Recommended 90hz - Up

SUBWOOFER	
DRIVER	2 x 15" Radial Bass Drivers
CONINUOUS OUTPUT	132db
PEAK OUTPUT	135db
DIMENSIONS	40"H x 18"W x 24"D
WEIGHT	157 lbs
RATED IMPEDANCE	2ohm
FREQUENCY RESPONSE	32 - 750 hz
POWER RATING	1000w AES
CROSSOVER	Recommended 30 hz to 500 hz

PURE GROOVE SOUND SYSTEMS